



## Solbrake

### DC Injection Brake

10 - 820A, 208 - 690V

The Solbrake Electronic brake provides fast, smooth, frictionless braking of standard three phase AC motors by injecting controlled DC current into the motor windings after the line contactor has opened. This DC current induces a stationary magnetic field which exerts a braking torque on the rotor. The Solbrake is an ideal replacement for old electro-mechanical braking systems including reversing or regenerative braking.

### Applications

- Machine tools
- Circular saws
- Stopping high inertia loads
- Safety brakes
- Large flywheel applications

### Advanced Features

- Reduces stopping time of high inertia loads
- Adjustable braking time
- Auto stop - DC Injection stops when the motor stops
- DIN Rail mounting (Rated current 10A)
- Easy to install and simple to operate
- Increases production rate in machine tools and high inertia loads
- Increases safety of hazardous machines
- Soft, smooth stopping, preventing wear and tear of mechanical parts
- Adjustable braking torque, matching load size and required stop time
- Auto stop, reducing motor heating
- Maintenance free, reliable operation

### Settings

- Braking torque - Determines the DC current level injected into the motor windings
- Two operation modes:
  - Auto mode: DC Injection automatically ends when motor stops
  - Manual mode: DC Injection ends after a pre-set braking time. This mode can be used to briefly "hold" the load at stand still

**For more information,  
 please contact:**

#### Rick Ligeikis

Phone: +1 304 523 4700  
 Cell: +1 864 314 9046  
 Fax: +1 304 523 4039  
 Home Fax: +1 864 225 5512  
[rligeikis@samincoinc.com](mailto:rligeikis@samincoinc.com)

#### Ed McFall

Phone: +1 304 523 4700  
 Cell: +1 304 638 7994  
[emcfall@samincoinc.com](mailto:emcfall@samincoinc.com)

#### Kenny Boles

Phone: +1 239 561 1561  
 Cell: +1 304 634 3380  
[kboles@samincoinc.com](mailto:kboles@samincoinc.com)



# Solbrake

DC Injection Brake

10 - 820A, 208 - 690V



Models | 10 - 820A, 208-690V

The Solbrake should be selected according to the motor's nominal current and starting conditions. For severe duty applications it is recommended that you select the next higher amperage rated unit.

Model	Rated Current (A)	Motor kW @400V	Unit Dimensions (mm)			Weight (kg)
			H	W	D	
A	10	5	75	45	105	0.7
B	17	7.5	190	65	114	1.4
	31	15				
	58	30				
C	105	55	280	154	160	5.2
	210	90				5.7
D	310	110	384	224	222	12
	390	160				
	460	220				
E	820	470	384	224	222	13.2

## How to Order

Example:

Solbrake - **31A** - **400V** - **8**

↓                      ↓                      ↓

Rated Current      Mains Voltage      Options

230V, 400V, 440V  
480V, 600V, 690V

8 - Conformal coating  
E - 30 sec braking time  
0 - Standard



Meeting your needs across industries



WATER



OIL & GAS



INDUSTRY



MINING



MARINE



For More Information

 [www.solcon.com](http://www.solcon.com)

 [contact@solcon.com](mailto:contact@solcon.com)

For more information,  
please contact:

**Rick Ligeikis**

Phone: +1 304 523 4700

Cell: +1 864 314 9046

Fax: +1 304 523 4039

Home Fax: +1 864 225 5512

[rligeikis@samincoinc.com](mailto:rligeikis@samincoinc.com)



**Ed McFall**

Phone: +1 304 523 4700

Cell: +1 304 638 7994

[emcfall@samincoinc.com](mailto:emcfall@samincoinc.com)

**Kenny Boles**

Phone: +1 239 561 1561

Cell: +1 304 634 3380

[kboles@samincoinc.com](mailto:kboles@samincoinc.com)